

INSTALLATION INSTRUCTIONS FOR PAD MOUNTED POST

EASY INSTALLATION INSTRUCTIONS

- Remove cover "A" by removing (4) screws "B". Slide cover slightly towards bottom of post (allowing top of cover to clear top retaining bracket) and pull cover away from post.
- Remove bag parts/mounting brackets from post assembly. Bag part contents:
 - (2) mounting brackets ("L" shaped)
 - (4) 3/8"-24 X 3/4" hex head screws
 - (4) 3/8" nuts
 - (8) 3/8" flat washers
- Location "G" - When load conductors exit the bottom of the post, remove the small horizontal barrier and rotate 90° to form a vertical barrier inside the post. Reassemble using the same screw and mounting hole. When load conductors exit K.O. use suitable conduit connector for outdoor applications.
- Install (2) mounting brackets on inside of post with screws, nuts, and washers described above (see diagram). NOTE: Use flat washers on inside and outside of post to protect paint finish.
- Attach post to pad using blot pattern dimensions shown in diagram (use mounting template on reverse side of this instruction if desired - installation requires (4) 3/8" minimum bolts and washers which are not supplied.)
- Lay wires in and attach to terminal bar. (see wiring diagram in post trough for torque and wire size information.)
- Place cover "A" back on post and fasten with (4) mounting screws "B" Lock or seal at "D".
- For added sealing options, order: SLKT1 (sealing screw kit)

FOR INSTALLATION OF TELEPHONE AND/OR TELEVISION OUTLETS, USE TTV BRACKET (NOT INCLUDED – ORDER SEPARATELY)

CAUTION PROCEDURE FOR ALL ALUMINUM TERMINATIONS

The following procedure is recommended when connecting aluminum wire.

- Strip the insulation, being careful not to nick the wire.
- Wire brush the conductor strands.
- Thoroughly coat the striped conductor with a suitable anti-oxidant compound such as alnox or penetrox A13.
- Insert conductor and tighten connector (See wiring diagram in post trough for torque and wire size information.)

