

SensyTemp TSH200

Straight thermocouples



Measurement made easy

TSH210
TSH220

Introduction

Straight thermocouple for high temperature applications such as industrial furnaces or combustion and smelting processes. Communication via FOUNDATION Fieldbus, PROFIBUS PA, HART, 4 to 20 mA or directly via the sensor output

Additional Information

Additional documentation on SensyTemp TSH200 is available for download free of charge at www.abb.com/temperature. Alternatively simply scan this code:



Table of contents

1	Safety	3
	General information and instructions	3
	Warnings	3
	Intended use.....	4
	Improper use.....	4
	Warranty provisions.....	4
	Manufacturer's address	4
2	Product identification	5
	Name plate	5
3	Transport and storage	6
	Unpacking the device	6
	Inspection	6
	Transporting the device.....	6
	Storage conditions	6
	Returning devices.....	6
4	Installation	7
	General information.....	7
	Installation instructions	7
	Ambient temperature.....	7
	Mounting position.....	7
	Mounting in installations at operating temperature.....	7
	Gas tightness	8
	Requirements for achieving the IP rating	8
	Electrical connections	8
	Safety instructions for electrical installation.....	8
	General	9
	Cable selection.....	9
	Conductor cross-section	9
	Connection to intrinsically safe circuits.....	9
	Electrical connections	10
	Connection on the device	11
5	Commissioning	12
	General	12
	Checks prior to commissioning.....	12
6	Maintenance / Repair	12
	Safety instructions.....	12
7	Recycling and disposal	13
	Dismounting.....	13
	Disposal.....	13
8	Specification	13
9	Additional documents	13
10	Appendix	14
	Return form	14

1 Safety

General information and instructions

These instructions are an important part of the product and must be retained for future reference.

Installation, commissioning, and maintenance of the product may only be performed by trained specialist personnel who have been authorized by the plant operator accordingly. The specialist personnel must have read and understood the manual and must comply with its instructions.

For additional information or if specific problems occur that are not discussed in these instructions, contact the manufacturer.

The content of these instructions is neither part of nor an amendment to any previous or existing agreement, promise or legal relationship.

Modifications and repairs to the product may only be performed if expressly permitted by these instructions.

Information and symbols on the product must be observed.

These may not be removed and must be fully legible at all times.

The operating company must strictly observe the applicable national regulations relating to the installation, function testing, repair and maintenance of electrical products.

Warnings

The warnings in these instructions are structured as follows:

DANGER

The signal word '**DANGER**' indicates an imminent danger. Failure to observe this information will result in death or severe injury.

WARNING

The signal word '**WARNING**' indicates an imminent danger. Failure to observe this information may result in death or severe injury.

CAUTION

The signal word '**CAUTION**' indicates an imminent danger. Failure to observe this information may result in minor or moderate injury.

NOTICE

The signal word '**NOTICE**' indicates possible material damage.

Note

'**Note**' indicates useful or important information about the product.

... 1 Safety

Intended use

The temperature sensors are used for temperature measurement in a wide variety of high-temperature applications up to 1800 °C (3272 °F).

The device is designed for use exclusively within the values stated on the name plate and in the specification (see **Specification** in the operating instruction or data sheet).

- The maximum operating temperature may not be exceeded.
- The maximum ambient temperature may not be exceeded.
- The IP rating must be observed during operation.

Before using the devices with corrosive or abrasive measuring media, the owner must check the level of resistance of all wetted parts. ABB Automation Products GmbH will gladly support you in selecting the appropriate device, but cannot accept any liability in doing so.

When using measuring media, the following items need to be considered:

- Measuring media may only be used if, based on the state of the art or the operating experience of the user, it can be assured that the chemical and physical properties necessary for operational security of the materials of the wetted parts of the temperature sensor will not be adversely affected during the operating time.
- Measuring media with unknown properties or abrasive measuring media may only be used if the operator is able to perform regular and suitable tests to ensure the safe condition of the device

Improper use

The following are considered to be instances of improper use of the device:

- For use as a climbing aid, for example for mounting purposes.
- For use as a bracket for external loads, for example as a support for piping, etc.
- Material application, for example by painting over the housing, name plate or welding/soldering on parts.
- Material removal, for example by spot drilling the housing.

Warranty provisions

Using the device in a manner that does not fall within the scope of its intended use, disregarding this manual, using underqualified personnel, or making unauthorized alterations releases the manufacturer from liability for any resulting damage. This renders the manufacturer's warranty null and void.

Manufacturer's address

ABB Automation Products GmbH Measurement & Analytics

Schillerstr. 72
32425 Minden
Germany
Tel: +49 571 830-0
Fax: +49 571 830-1806

Customer service center

Tel: +49 180 5 222 580
Email: automation.service@de.abb.com

2 Product identification

Name plate

Note

The name plates displayed are examples. The device identification plates affixed to the device can differ from this representation.




Figure 1: Name plate (example)

Note

Optionally, an approval plate can be present as well. The approval plate contains information concerning the corresponding approval, such as, for example Approval number, type designation in accordance with the approval or indicates a manufacturer declaration.

Note

The values specified on the name plate are maximum values and do not take process-related stress into consideration. This should be taken into consideration when working with the instruments.

Note



Products that are marked with the adjacent symbol may **not** be disposed of as unsorted municipal waste (domestic waste). They should be disposed of through separate collection of electric and electronic devices.

3 Transport and storage

Unpacking the device

NOTICE

Damage to the device due to improper handling!

Ceramic thermowells are fragile and be damaged due to improper handling.

- Handle the temperature sensor with caution and avoid any kind of mechanical shock or impulse.

Note the following items when unpacking the devices:

- Take special care when unpacking the devices to prevent any damage.
- Check the packing and packing material for accessories.
- For temperature sensors with flange, remove the transport lock in accordance with the accompanying instruction.

Inspection

Check the devices immediately after unpacking for possible damage that may have occurred from improper transport.

Details of any damage that has occurred in transit must be recorded on the transport documents.

All claims for damages must be submitted to the shipper without delay and before installation.

Transporting the device

Observe the following instructions:

- Do not expose the device to humidity during transport. Pack the device accordingly.
- Pack the device so that it is protected against vibrations during transport, for example, by using air-cushioned packing.

Storage conditions

Bear the following points in mind when storing devices:

- Store the device in its original packing in a dry and dust-free place.
- The storage temperature should be in the range of -20 to 70°C (-4 to 158°F).
- After longer periods of storage, check the gaskets and replace, if necessary, prior to use.
- In principle, the devices may be stored for an unlimited period. However, the warranty conditions stipulated in the order confirmation of the supplier apply.

Returning devices

Use the original packaging or a secure transport container of an appropriate type if you need to return the device for repair or recalibration purposes.

Fill out the return form (see **Return form** on page 14) and include this with the device.

In accordance with the EU Directive governing hazardous materials, the owner of hazardous waste is responsible for its disposal or must observe the following regulations for shipping purposes:

All devices delivered to ABB must be free from any hazardous materials (acids, alkalis, solvents, etc.).

Please contact Customer Center Service acc. to page 4 for nearest service location.

4 Installation

WARNING

Risk of injury due to process conditions.

The process conditions, for example high pressures and temperatures, toxic and aggressive measuring media, can give rise to hazards when working on the device.

- Before working on the device, make sure that the process conditions do not pose any hazards.
- If necessary, wear suited personal protective equipment when working on the device.
- Depressurize and empty the device / piping, allow to cool and purge if necessary.

NOTE

Damage to the device due to improper handling!

Ceramic thermowells are fragile and be damaged due to improper handling.

- Handle the temperature sensor with caution and avoid any kind of mechanical shock or impulse.

General information

- The temperature sensor (thermocouple) must have optimal contact with the measuring medium.
- The IP rating will no longer apply in the event of damage to the connection head or the threads, gaskets or cable glands on the connection head.
- The connection leads must be firmly connected to the terminals.
- The correct polarity must be ensured in the case of thermocouples.
- When installing temperature sensors in existing thermowells, make sure that the temperature sensor can be inserted easily. If this is not the case, the inside of the thermowell will need to be cleaned.
- When installing exchangeable measuring insets in existing thermowells, make sure that the measuring inset can be inserted easily. If this is not the case, the inside of the thermowell will need to be cleaned.
- The temperature sensor must be firmly and securely installed in a way that conforms to the requirements of the application process.
- Please take note of the sensor and circuit type specified.

- After clamping the connection leads using a suited tool (screwdriver, wrench), you must make sure that the connection heads are securely closed and sealed again. When doing this, make sure that the sealing rings of the connection heads are clean and undamaged.
- The gaskets should be selected and correctly installed in accordance with the requirements.
- In devices with flange process connections, evenly tighten the flange screws in a cross wise manner.

Installation instructions

Ambient temperature

Design	Ambient temperature
Connection head without transmitter and with suited cable gland	-40 to 120 °C (-40 to 248 °F):
Connection head with transmitter	-40 to 85 °C (-40 to 185 °F):

In specific applications, high temperature sensors are frequently subjected to higher temperatures at the connection head. In temperature sensors with cable glands, the supplied cable gland (thread M20 × 1.5) is fitted with a silicon thrust collar instead of a rubber thrust collar.

Mounting position

For high process temperatures, we recommend a vertical mounting position of the temperature sensor to protect against bending and prevent mechanical damage to the thermowell. If the temperature sensor can only be mounted in a horizontal mounting position, the thermowell should be supported.

Mounting in installations at operating temperature

Ceramic thermowells are characterized by a high level of hardness and brittleness. If ceramic thermowells are exposed to temperature shock, they can crack due to internal stress in their grain structure.

For this reason, temperature sensors with ceramic thermowells may only be introduced gradually into the process:

Process temperature	Slide-in rate
≤ 1600 °C (≤ 2912 °F)	1 to 2 cm/min (0.4 to 0.8 in/min)
≤ 1200 °C (≤ 2192 °F)	10 to 20 cm/min (3.9 to 7.8 in/min)

... 4 Installation

... Installation instructions

Gas tightness

Gas-tight ceramic materials are typically only resistant to temperature changes on a limited basis. To reduce the risk of temperature shock and prevent the thermowell from subsequently bursting, temperature sensors with gas-tight ceramic thermowells must be heated before installation.

High temperature sensors are generally designed for use in pressureless processes.

When fastening the temperature sensor using limit stop flanges and counterflanges, a pressure of up to approx. 1 bar (14.50 psi) of gas tightness can be assumed with proper installation. Refer to EN 50446 in this regard.

Requirements for achieving the IP rating

The temperature sensor SensyTemp TSH200 can be supplied with a M20 × 1.5 or ½ in NPT thread.

When selecting the appropriate cable gland, the user must take suited measures to make sure that the required IP rating is achieved, the temperature range maintained and that the cable gland used is in accordance with the standard on which the present certificate is based.

To achieve the IP rating, the cable gland used must be approved for the cable diameter. In practice, you may find the specified IP rating can no longer be achieved if certain cables and lines are used in conjunction with the cable gland.

Deviations from the test conditions as set out in the IEC 60529 standard must be checked. Check the cables' concentricity, transposition, external hardness, sheath, and surface roughness.

The operating temperature range of the cable gland used must not be up-scaled.

Observe tightening torque in accordance with information in the data sheet / operating instruction of the cable gland used.

Please observe the following points:

- Only use cable glands in the specified clamping area.
- When using very soft cable types, do not use them in the lower clamping area.
- Only use round cables or cables with a slightly oval-shaped cross section.
- Frequent opening / closing is possible but may have a negative effect on the IP rating.
- If cables are demonstrating pronounced cold flow behavior, the cable glands will need to be retightened.
- Cables with VA wire mesh require special cable glands.

Electrical connections

Safety instructions for electrical installation

WARNING

Risk of injury due to live parts.

Improper work on the electrical connections can result in electric shock.

- Connect the device only with the power supply switched off.
- Observe the applicable standards and regulations for the electrical connection.

The electrical connection may only be established by authorized specialist personnel.

Notices on electrical connection in this instruction must be observed; otherwise, electric safety and the IP-rating may be adversely affected.

Safe isolation of electric circuits which are dangerous if touched is only guaranteed when the connected devices fulfill the requirements of EN 61140 (basic requirements for secure separation).

To ensure safe isolation, install supply lines so that they are separate from electrical circuits which are dangerous if touched, or implement additional isolation measures for them.

General

The following applies to devices with a transmitter:

- The power supply and signal are routed in the same conductor and should be implemented as a SELV or PELV circuit in accordance with the relevant standard (standard version).
- In devices for use in non-hazardous areas with intrinsically safe electronic units connected (for example Transmitters), guidelines in accordance with the Ex standard.
- The temperature sensor and transmitter do not have any kind of turn-off device, therefore over-current protective devices and lightning protection or voltage separation capacity must be provided in the installation.
- The power supply data must match the information on the name plate.
- The user is responsible for ensuring EMC-compliant cabling.

Cable selection

When selecting the connection cable, observe the following points:

- Only use insulated cables and wires in which the test voltage between wire – ground, wire – shielding, and shielding – ground is at least 500 V AC.
- Provide cables with wire end ferrules.
- The cables used must fulfill the valid requirements with regards to strength and temperature for the particular application case.
- Install the cable in a manner that will rule out any mechanical damage.
- When using PROFIBUS® the design should be in accordance with EN 50170.
- When using FOUNDATION Fieldbus® the design should be in accordance with IEC 61158.

Conductor cross-section

The maximum connectible conductor cross-section is 1.5 mm² (15 AWG).

Connection to intrinsically safe circuits

DANGER

Explosion hazard due to improper installation!

An explosion hazard is present when installing the SensyTemp TSH200 temperature sensor in potentially explosive atmospheres.

- The SensyTemp TSH200 temperature sensor may only be installed and operated outside of potentially explosive atmospheres.

Note

- When connecting the temperature sensor to intrinsically safe circuits, please comply with the **'Manufacturer's declaration on connection to attested intrinsically safe circuits'**!
- When connecting temperature sensors with dual sensor elements (2 × thermocouple) to an intrinsically safe circuit, only a measuring loop may be connected!

If the SensyTemp TSH200 temperature sensors are operated in intrinsically safe circuits in Ex ia / Ex ib type of protection, proof that the interconnection is intrinsically safe must be provided in accordance with DIN VDE 0165/Part 1 (EN 60079-25 as well as IEC 60079-25).

The supply isolators / DCS inputs must feature intrinsically safe input circuits to eliminate hazards (spark formation).

In order to provide proof of intrinsic safety, the electrical limit value must be used as the basis for the EC-type examination certificates for the equipment (devices); this includes the capacitance and inductance values of the cables.

These requirements guarantee that operation of a SensyTemp TSH200 temperature sensor in an intrinsically safe circuit does not cancel its intrinsic safety.

The SensyTemp TSH200 temperature sensor which will be used in an intrinsically safe circuit shall be supplied with a **'Manufacturer's declaration on connection to attested intrinsically safe circuits'**.

If two transmitters are used for two intrinsically safe circuits, the sum of the values may not up-scale the maximum values specified in the operating instruction and the **'Manufacturer's declaration on connection to attested intrinsically safe circuits'**.

... 4 Installation

... Electrical connections

Electrical connections


The temperature sensors may be fitted with single or dual thermocouples.

When using the temperature sensors in intrinsically safe circuits, only attested transmitters with maximum electric values as specified in the operating instruction or the **'Manufacturer's declaration on connection to attested intrinsically safe circuits'** may be connected.


SensyTemp TSH210, AM and AMK designs – thermocouples K, J, N, L

SensyTemp TSH220, AK and AKK designs – thermocouples K, J, N, L

Single sensor




Double sensor




SensyTemp TSH210, AM and AMK designs – thermocouples R, S, B

SensyTemp TSH220, AK and AKK designs – Thermocouples R, S, B

Single sensor




Double sensor




SensyTemp TSH210, BM and BMK designs – thermocouples K, J, N, L, R, S, B

SensyTemp TSH220, BK designs – thermocouples K, J, N, L, R, S, B

Single sensor



Double sensor



Connection on the device

Temperature sensor without integrated transmitter

Use a suited compensating cable to connect the temperature sensor without integrated transmitter!

1. Switch off the temperature sensor power supply.
2. Open the connection head. Observe the cool down time!
3. Connect the positive wire of the compensating cable with the terminal on the transmitter marked “+” and the negative wire of the compensating cable with the terminal marked ‘-’.
4. Establish a grounding connection if necessary.
5. The screws must be fastened tight and proper contact guaranteed.
6. Tightly close the connection head.

Temperature sensor with integrated transmitter

In temperature sensors with integrated transmitters, the sensor is already connected to the transmitter at the factory.

Connection of the transmitter is described in the appropriate corresponding operating instruction. The technical data of the selected transmitter must be complied with.

For Fieldbus applications, please comply with the installation recommendations 10/63-0.40 (PROFIBUS PA®) and 10/63-0.50 (FOUNDATION Fieldbus®)!

The operating instruction for the selected transmitter is included in the delivery.

Alternatively, all documentation is available for download free of charge at www.abb.com/temperature.

5 Commissioning

General

The device is immediately ready for operation after mounting and installation of the connections. Default parameters are set at the factory.

Checks prior to commissioning

Note

Detailed information on operating the transmitter is available in the operating instruction of the transmitter.

The following points must be checked before commissioning the device:

- The proper mounting and sealing of thermowells or protective sleeves.
- The potential equalization line must be connected.
- The electric specifications must comply with the specified values.
- Assembly and electrical connection must be conducted professionally in accordance with **Installation** on page 7.

6 Maintenance / Repair

Safety instructions

WARNING

Risk of injury due to process conditions.

The process conditions, for example high pressures and temperatures, toxic and aggressive measuring media, can give rise to hazards when working on the device.

- Before working on the device, make sure that the process conditions do not pose any hazards.
- If necessary, wear suited personal protective equipment when working on the device.
- Depressurize and empty the device / piping, allow to cool and purge if necessary.

NOTE

Damage to the device due to improper handling!

Ceramic thermowells are fragile and be damaged due to improper handling.

- Handle the temperature sensor with caution and avoid any kind of mechanical shock or impulse.

Note

For detailed information on the maintenance of the device, consult the associated operating instructions (OI)!

7 Recycling and disposal

Dismounting

WARNING

Risk of injury due to process conditions.

The process conditions, for example high pressures and temperatures, toxic and aggressive measuring media, can give rise to hazards when dismantling the device.

- If necessary, wear suited personal protective equipment during disassembly.
- Before disassembly, make sure that the process conditions do not pose any safety risks.
- Depressurize and empty the device / piping, allow to cool and purge if necessary.

Bear the following points in mind when dismantling the device:

- Switch off the power supply.
- Disconnect electrical connections.
- Allow the device / piping to cool and depressurize and empty. Collect any escaping medium and dispose of it in accordance with environmental guidelines.
- Use suited tools to disassemble the device, taking the weight of the device into consideration.
- If the device is to be used at another location, the device should preferably be packaged in its original packing so that it cannot be damaged.
- Observe the notices in **Returning devices** on page 6.

Disposal

Note



Products that are marked with the adjacent symbol may **not** be disposed of as unsorted municipal waste (domestic waste).

They should be disposed of through separate collection of electric and electronic devices.

This product and its packaging are manufactured from materials that can be recycled by specialist recycling companies.

Bear the following points in mind when disposing of them:

- As of 8/15/2018, this product will be under the open scope of the WEEE Directive 2012/19/EU and relevant national laws (for example, ElektroG - Electrical Equipment Act - in Germany).
- The product must be supplied to a specialist recycling company. Do not use municipal waste collection points. These may be used for privately used products only in accordance with WEEE Directive 2012/19/EU.
- If there is no possibility to dispose of the old equipment properly, our Service can take care of its pick-up and disposal for a fee.

8 Specification

Note

The device data sheet is available in the ABB download area at www.abb.com/temperature.

9 Additional documents

Note

All documentation, declarations of conformity, and certificates are available in ABB's download area.

www.abb.com/temperature

10 Appendix

Return form

Statement on the contamination of devices and components

Repair and/or maintenance work will only be performed on devices and components if a statement form has been completed and submitted.

Otherwise, the device/component returned may be rejected. This statement form may only be completed and signed by authorized specialist personnel employed by the operator.

Customer details:

Company: _____

Address: _____

Contact person: _____ Telephone: _____

Fax: _____ Email: _____

Device details:

Type: _____ Serial no.: _____

Reason for the return/description of the defect: _____

Was this device used in conjunction with substances which pose a threat or risk to health?

Yes No

If yes, which type of contamination (please place an X next to the applicable items):

biological corrosive / irritating combustible (highly / extremely combustible)

toxic explosive other toxic substances

radioactive

Which substances have come into contact with the device?

1. _____

2. _____

3. _____

We hereby state that the devices/components shipped have been cleaned and are free from any dangerous or poisonous substances.

Town/city, date

Signature and company stamp

Trademarks

HART is a registered trademark of FieldComm Group, Austin, Texas, USA

PROFIBUS and PROFIBUS PA are registered trademarks of PROFIBUS & PROFINET International (PI)

FOUNDATION Fieldbus is a registered trademark of FieldComm Group, Austin, Texas, USA.

ABB Limited

Measurement & Analytics

Howard Road, St. Neots
Cambridgeshire, PE19 8EU
UK

Tel: +44 (0)870 600 6122

Fax: +44 (0)1480 213 339

Email: enquiries.mp.uk@gb.abb.com

ABB Inc.

Measurement & Analytics

125 E. County Line Road
Warminster, PA 18974
USA

Tel: +1 215 674 6000

Fax: +1 215 674 7183

ABB Automation Products GmbH

Measurement & Analytics

Schillerstr. 72
32425 Minden
Germany

Tel: +49 571 830-0

Fax: +49 571 830-1806

abb.com/temperature

We reserve the right to make technical changes or modify the contents of this document without prior notice. With regard to purchase orders, the agreed particulars shall prevail. ABB does not accept any responsibility whatsoever for potential errors or possible lack of information in this document.

We reserve all rights in this document and in the subject matter and illustrations contained therein. Any reproduction, disclosure to third parties or utilization of its contents – in whole or in parts – is forbidden without prior written consent of ABB.

Copyright© 2018 ABB

All rights reserved

3KXT141001R4401