


On-load tap-changer type UCGD./III, VUCGD./III, UCLD./III, VUCLR./III, UCDD./III, 11 tap positions, coarse/fine switching.
 Min. effective No. of turns in pos. 1.
 The tap-changer is delivered set in pos. 6,
 the preceding pos. was 5.

Lindningskopplare typ UCGD./III, VUCGD./III, UCLD./III, VUCLR./III, UCDD./III, 11 lägen, grov/fin koppling.
 Min antal effektiva varv i läge 1.
 Lindningskopplaren levereras inställd i läge 6,
 föregående läge var 5.

Pos. Läge	R connects in direction R förbinder i riktning	Tap selector and diverter switch connect Väljaren och lastkopplaren förbinder
1	↓	11-V-x
2		10-H-v
3		9-V-x
4		8-H-v
5		7-V-x
6	↓	6-H-v
7	↑	5-V-x
8		4-H-v
9		3-V-x
10		2-H-v
11		1-V-x



We reserve all rights in this document and in the information contained therein. Reproduction, use or disclosure to third parties without express authority is strictly forbidden. © ABB '19

The tap-changer is shown in pos. 6,
 the preceding pos. was 5.
 The tap selector and the change-over selector
 are seen from above.
 Contact arm V is located above contact arm H.

Lindningskopplaren visad i läge 6,
 föregående läge var 5.
 Väljaren och grov/fin-omkopplaren sedda uppifrån.
 Kontaktarm V ligger över kontaktarm H.

Continuous lines show leads included in the
 tap-changer. Dashed lines show leads belonging
 to the cleats and leads.

Heldragna linjer visar ledare som ingår i
 lindningskopplaren. Streckade linjer visar
 ledare som tillhör anslutningsdonet.

2	VUCL Added.	CA	12	37
1	VUCG Added.	THLA	07	47
Rev Ind	Revision	Appd	Year	Week

Accepted by qual control R.Yngvesson	Accepted for prod by	Description (English) CONNECTION DIAGRAM	DATAORIGINAL
Design checked by B-O.Stenestam	Drawn by L.Bergman	Description (own language) KOPPLINGSSHEMA	File name 0372-2
Drawing checked by M.Hedlund	Issued by Dept Year Week COM/TKO 97 23	5492 0372-2	Lang Sheet 1
Asea Brown Boveri			Revind Cont -