



CAT.NO.	XT1ENCL125F	1SQA001264R0001	FLUSH MOUNTED	INDOOR, TYPE 1	USE 75° C CONDUCTORS
	XT1ENCL125S	1SQA001265R0001	SURFACE MOUNTED		
FOR USE WITH CIRCUIT BREAKER TYPES: TMAX XT1					WARNING INSTRUCTIONS: DANGER OF ELECTRICAL SHOCK OR BURN. TURN OFF POWER AHEAD OF CIRCUIT BREAKER BEFORE WORKING INSIDE. AFTERWARDS, REPLACE ALL PARTS,CLOSE AND SECURE COVER.
ENCLOSURE AND NEUTRAL RATING 125A, 480V MAX.					
SUITABLE FOR USE AS SERVICE EQUIPMENT					
REPLACEMENT PARTS					
NEUTRAL CATALOG NUMBER		AMPERE RATING	WIRE SIZE (AWG/KCMIL)		AVERTISSEMENT: RISQUE DE CHOC ELECTRIQUE ET DE TRANSFERT D'ENRGIE. COUPER L'ALIMENTATION EN AMONT DU DISJONCTEUR AVANT D'EFFECTUER DES TRAVAUX A L'INTERIER. REPOSER TOUTES LES PIECES APRES LES TRAVAUX. FERMER ET VERROUILLER LE COUVERCLE.
TNIA225 MOD.9		25-125A	(1) #14-1 CU (1) #12-2/0 AL		
FOR USE WITH CU-AL CONDUCTORS WHEN BREAKER AND NEUTRAL ARE SO MARKED					
EQUIPMENT GROUND	AMPERE RATING	WIRE SIZE (AWG/KCMIL)			
TGL1	70-125A	(4) #14-8 CU (4) #12-8 AL (3) #14-4 CU (3) #6-4 AL			
FOR USE WITH CU-AL CONDUCTORS WHEN BREAKER AND NEUTRAL LUGS ARE SO MARKED					ALUMINUM WIRE CAN CAUSE OVER HEATING. STEPS FOR CONNECTING ALUMINUM WIRE: (1) STRIP INSULATION WITHOUT NICKING WIRE. (2) WIRE BRUSH CONNECTORS STRANDS. (3) COAT STRANDS WITH ANTI-OXIDANT SUCH AS ALNOX OR PENETROX A13. (4) INSERT CONDUCTORS AND TIGHTEN SECURELY.
CIRCUIT BREAKER LUGS: ORDER (1) KIT EACH FOR LINE AND LOAD END					
AMPERE	BREAKER LUG CATALOG NUMBER		WIRE SIZE (AWG/KCMIL)		THE SHORT CIRCUIT WITHSTAND OF THIS ENCLOSURE IS EQUAL TO THE RATING OF THE BREAKER INSTALLED. SEE BREAKER FOR INTERRUPTING RATINGS.
125A	KXT1CU-3PC	KXT1CU-4PC	(1) #14-1/0 CU		
	KXT1CUAL1-3PC	KXT1CUAL1-4PC	(1) #10-2/0 CU-AL		
ASSEMBLED IN MEXICO					



PRODUCT RATING LABEL
 CATALOG XT1ENCL125S,XT1ENCL125F

THIRD ANGLE	SHEET#	DWG NO.	DATE	REV
	1 of 1	1SQC930119M0201	27-May-22	3