


FurseWELD

Cable to reinforcing bar CRE1

Cable to reinforcing bar CRE1 - FurseWELD

	Reinforcing bar size A \varnothing (mm)	Stranded/solid circular conductor size B (mm ²)	Mould part no.	Order code	Powder cartridge part no.	Handle clamp part no.	Packing part no.
	10-40	16 *	CRE1-3-16	7TCA083910R1830	45P10	HCPK3-B	PACK-A
	10-40	25	CRE1-3-25	7TCA083910R1831	45P10	HCPK3-B	PACK-A
	10-40	35	CRE1-3-35	7TCA083910R1832	45P10	HCPK3-B	PACK-A
	10-40	\varnothing 8	CRE1-3-8SC	7TCA083910R1835	90P10	HCPK3-B	PACK-A
	10-40	50	CRE1-3-50	7TCA083910R1833	90P10	HCPK3-B	PACK-A
	10-40	70	CRE1-3-70	7TCA083910R1834	90P10	HCPK3-B	PACK-A
	10-40	95	CRE1-3-95	7TCA083910R1836	90P10	HCPK3-B	PACK-A
	10-40	120	CRE1-3-120	7TCA014980R0153	90P10	HCPK3-B	PACK-A

Special moulds for all FurseWELD products can be manufactured to meet specific customer applications on request

*1 x S103 Sleeve required when joining conductors 16 mm² or smaller

For order codes of powder cartridges, handle clamps and packing, see pages 49-50

FurseWELD moulds should only be used with FurseWELD powders, handle clamps and accessories. If moulds, powders, handle clamps and accessories from other manufacturers are utilized, we cannot guarantee the safe use or the integrity of the completed joint

FurseWELD moulds for use with stranded conductor are designed for use with non-compacted conductor to BS EN 60228. If a mould for compacted conductor is required, please contact your local representative

Conductors must be installed in the orientation shown to achieve the correct connection