



DATA SHEET

Ready with MEG changes

MEG Approved products



As of July 1, 2016, the Meter Equipment Group (MEG) have new requirements. Our products meet the new requirements and are ready to go! Contact your salesperson to place your order.

A new utility group has been created called Meter Equipment Group (MEG). MEG consists of the following utilities:

- Florida Power & Light (Florida)
- Tampa Electric (Florida)
- Gulf Power (Florida)
- Oklahoma Gas & Electric (Oklahoma)
- Duke Energy (Florida, North and South Carolina, Indiana, Ohio and Kentucky)


MEG has begun to standardize their spec concerning our meter socket load center, Mini Mod™ and Meter Mod™ III product lines.

Effective July 1, 2016, MEG have new specifications for the residential Mini Mod and Meter Mod units (TMM, TMMR, TMP, TMPR), this includes additional requirements on the construction of the socket assembly. They now require a cotter pin (really a spring type pin) that gets inserted into the meter stabs. This helps prevent the meter from coming loose from the stabs.

This change is applicable on the 125A and 200A plug-in style meter sockets without lever bypass and includes both ring and ringless designs. This change

is going into effect 7/1/2016 for locations outside of Florida (the Florida team implemented this earlier in the year).

We received approval from MEG for a new set of catalog numbers, identified with the “F” suffix, for the Mini Mod and Meter Mod III product families. These new catalog numbers indicate that the socket base has cotter pins installed through the jaws as shown in the photo below.



The MEG approved units have an added cotter pin that eliminates failure of the metering stabs when the meter is plugged into the meter base.

Mini Mod III

Ring-type and ringless

Mini Mod III

Ring-type and ringless - MEG Approved 125A and 200A sockets

- UL Listed (Panelboards No. 67)
- Indoor/outdoor construction
- Ring-type and ringless meter sockets
- Bondable neutral, strap included
- 11-inch mounting Z-rail included
- Swing away mounting feet factory installed
- Underground, incoming feed only



Socket Amps	No. of Sockets	Main Ampere Rating	Ring-Type Socket ¹ (4 Jaw Socket Standard)	Ringless Socket (5th Jaw Socket Standard)	Main Wire Size AWG/kcmil Cu/Al - Phase	Service Ground	Equipment Ground
125	2	200	TMM2212RF ²	TMMR2212RF ²	(1) 6-300	6-2/0	14-4
	3	400	TMM4312RF	TMMR4312RF	(1) 6-600 or (2) 2/0-250	4-300	
	4	400	TMM4412RF	TMMR4412RF			
	5	600	TMM6512RF	TMMR6512RF	(2) 250-500		
	6	600	TMM6612RF	TMMR6612RF			
200	2	400	Use TMM6320R	TMMR4220RF	(2) 250-500	6-2/0	14-4
	3	600	TMM6320RF	TMMR6320RF		4-300	
	4	600	TMM6420RF	TMMR6420RF			
	5	600	Use Ringless or Meter Mod III	TMMR6520RF			
	6	600	Use Ringless or Meter Mod III	TMMR6620RF			

¹One snap-type, aluminum sealing ring (TSR5) per socket included.

²May be fed from overhead. Use hub TC300.

Meter stack modules

Residential, single-phase

Meter stack modules

Residential, single phase - MEG Approved

800A and 1200A horizontal bussing

125A and 200A sockets

- 800 and 1200 amp, 4 wire crossbus (aluminum)
- UL Listed
- Front accessible field phase balancing by meter stack
- (1) 14-4 equipment ground per socket, factory installed
- Meter Equipment Group Approved



800A horizontal bussing 125A and 200A sockets

Socket Amps	No. of Sockets	Ring Type Socket (4 Jaw Socket Standard)	Ringless Type Socket (5th Jaw Socket Standard)	Ringless Type Socket (5th Jaw Socket Standard) Horned Bypass Factory Installed
125	2	TMP8212RF ¹	TMPR8212RF	TMPR8212RHBF
	3	TMP8312RF ¹	TMPR8312RF	TMPR8312RHBF
	4	TMP8412RF ¹	TMPR8412RF	TMPR8412RHBF
	5	TMP8512RF ¹	TMPR8512RF	TMPR8512RF + TMPBPH20A
	6	TMP8612RF ¹	TMPR8612RF	TMPR8612RF
200	2	Use TMP8320RF with bottom blank (TMCB12B)	TMPR8220RF	TMPR8220RF + TMPBPH20A
	3	TMP8320RF ¹	TMPR8320RF	TMPR8320RF + TMPBPH20A
	4	TMP8420RF ¹	TMPR8420RF	TMPR8420RHBF
	5	If allowed, use Ringless TMPR8520RF	TMPR8520RF	TMPR8520RF + TMPBPH20A

1200A horizontal bussing 125A and 200A sockets

Socket Amps	No. of Sockets	Ring Type Socket (4 Jaw Socket Standard)	Ringless Type Socket (5th Jaw Socket Standard)	Ringless Type Socket (5th Jaw Socket Standard) Horned Bypass Factory Installed
125	4	Use TMP12420RF	TMPR12412RF	TMPR12412RHBF
	5	If allowed, use Ringless TMPR12512RF	TMPR12512RF	TMPR12512RHBF
	6	If allowed, use Ringless TMPR12612RF	TMPR12612RF	Use TMPR12612RF + TMPBPH20A
200	4	TMP12420RF ¹	TMPR12420RF	TMPR12420RHBF
	5	If allowed, use Ringless TMPR12520RF	TMPR12520RF	Use TMPR12520RF + TMPBPH20A

¹One snap-type, aluminum sealing ring (TSR5) per socket included

PowerMark Gold™ meter socket load centers

Main Ampere Rating	1 Pole, 1" Spaces	2 Pole, 1" Spaces	1 Pole, 1/2" Spaces	2 Pole, 1/2" Spaces	Total 1-pole Spaces	Catalog Number	Socket Type	Enclosure	Feed-Thru Lugs	Front Type	Bypass Type	Bussing Type	UL Incoming	Agency Certification
Main Breaker / Ringless/ Single-Phase, 3 Wire, 120/240 Vac with Bonded Neutrals														
150	4	2	8	3	8	TSMR415CSFLFMG	Ringless	Outdoor (NEMA 3R)	Yes	Surface	None	Copper	OH/UG	UL/MEG
200	4	2	8	3	8	TSMR420CSFLFMG								
150	8	4	16	6	16	TSMR815CSFLFMG								
200	8	4	16	6	16	TSMR820CSFLFMG								
	20	4	40	18	40	TSMR2020CSCUFMG			No					
Class 320 / Ringless / Single-Phase, 3 Wire, 120/240 Vac with Bonded Neutrals														
300	8	4	16	6	16	TSDR830USCU	Ringless	Outdoor (NEMA 3R)	Yes	Surface	Lever Bypass	Copper	UG	UL/MEG
400	8	4	16	6	16	TSDR840UFUCU								
Meter Main Factory Installed / Ringless / Single-Phase, 3 Wire, 120/240 Vac with Bonded Neutrals														
100	0	0	0	0	0	TM10RMCFMG ¹	Ringless	Outdoor (NEMA 3R)	Yes	Surface	None	Copper	OH/UG	UL/MEG
125	0	0	0	0	0	TM12RMCFMG ¹								
150	0	0	0	0	0	TM15RMCFMG ¹								
200	0	0	0	0	0	TM20RMCFMG ¹								
Meter Socket Load Center / Ring-Type / Single-Phase, 3 Wire, 120/240 Vac														
150	4	2	8	3	8	TSMF415CSFL ¹	Ring-Type	Outdoor (NEMA 3R)	Yes	Surface	None	Copper	OH/UG	UL/MEG
		8	4	16	6	16								
200	4	2	8	3	8	TSMF420CSFL ¹								
	8	4	16	6	16	TSMF820CSFL ¹								
Meter Socket Load Center / Ringless / Single-Phase, 3 Wire, 120/240 Vac														
This is a Service Entrance MLO rated load center. No more than 6 circuits may be added in total in accordance with NEC code concerning service entrance load centers.														
200	6	6	0	0	0	TSLR1220FSAL	Ringless	Outdoor (NEMA 3R)	Yes	Flush	None	Aluminum	OH/UG	UL/MEG

¹ Devices include removable closing cap. Order hub separately

ABB Inc.
305 Gregson Drive
Cary, NC 27511
United States

electrification.us.abb.com

GE is a trademark of GE.
Manufactured by ABB Ltd under license from General Electric Company.

We reserve the right to make technical changes or modify the contents of this document without prior notice. With regard to purchase orders, the agreed particulars shall prevail. ABB Inc. does not accept any responsibility whatsoever for potential errors or possible lack of information in this document.

We reserve all rights in this document and in the subject matter and illustrations contained therein. Any reproduction, disclosure to third parties or utilization of its contents – in whole or in parts – is forbidden without prior written consent of ABB Inc. © 2022 ABB
All rights reserved

Mini Mod, Meter Mod and PowerMark Gold are trademarks of ABB Inc.