Shield oil-side
(Additional accessories)
LF 170 046-V or
LF 170 046-VP



Shield SF6-side
(Additional accessories)
LF 170 046-F



Pressure supervision equipment
LF 410 024-K or LF 410 024-L
(Additional accessories)



Terminal stud SF6-side
(Additional accessories)



LF 170 050-AA (AL)
or
LF 170 050-AL (Cu/Ag)

LF 170 050-AH





Flange SF6-side



Flange oil-side



Drawrod system



LF 124 103-B LF 124 103-E

Catalogue number: LF 124 003-B

Electrical data

Ratings	Rated voltage	550 kV
	Max phase to ground	318 kV
	Rated current Vertical	2500 A
	Rated current Horizontal	1600 A
Test voltages	Lighting impulse	1675 kV
	Switching impulse	1300 kV
Routine test	Power frequency	750 kV

ABB Components AB

Bushing GOEK 1675

No. Horiz 1600 A

Un/Uy 550/318 kV Vert 2500 A

Test LI/SI/AC 1675/1300/750 kV

Year L 1285 mm M 540 kg

PF %C1/C2 pF

Rev Ind	Revision	Appd Year	Week
1	340 added	96	9941

Accepted by qual	Accepted for prod by	Description (English): GOEK 1675 FE=300
Design checked by: Heyman	Drawn by: Andersson	Description (own language):
Drawing checked by: Jonsson	Issued by/Year-Week: COM/BK 94 31	2753 015-27

ABB ABB Components

DATAORIGINAL | File name | Lang | Sheet 1 | Rev | Cont -

Drawn by | Form No. | Sheet | Cont | Appl | Year | Week

We reserve all rights in this document and in the information contained therein. Reproduction, use or disclosure to third parties without express authority is strictly forbidden. © ABB 19